ALPINE SERVICE MANUAL

Power Amplifier



3521

Contents

Specifications 2
Parts Locations and Disassembly Instructions ..... 3 to 4
Adjustment Procedures 5
Adjustment Locations 6
Block Diagram 7
Parts Layout on P.C. Board ..... 8 to 10
Electrical Parts List ..... 11 to 14
Schematic Diagram ..... 15 to 16
Wiring Diagram ..... 17 to 18
Exploded View ..... 19 to 20
Mechanical Parts List 21
Packing Method View 22
Packing Parts List 23
Semiconductors Lead Identifications ..... 24 to 26

Specifications

Power Output (1 kHz, 8% THD)	58 W/CH
Rated Power Output (20 Hz ~ 20 kHz, 0.1% THD)	45 W/CH
Input Sensitivity (Rated Power Output)	500 mV ± 10%
Input Impedance	10K ohms ± 20%
Frequency Response (–1 dB at 1 W Output)	20 Hz to 20 kHz
Current Drain (Rated Power Output)	20 A
Channel Separation (at 1 kHz)	60 dB
Speaker Impedance	4 ohms or 2 ohms
Fuse Requirement	25 A (Battery) 3 A (ACC) 3 A (Battery)
Power Source	14.4 DC
Semiconductors	5 ICs, 29 Transistors, 24 Diodes, 6 Zener Diodes
Dimensions (WxHxD)	240 x 55 x 160 mm
Weight	2.2 kg

Parts Locations and Disassembly Instructions



Figure 1



Figure 2



Figure 3

1. Removal of Bottom Cover

(1) Remove two screws marked "○" in Figure 4.

2. Removal of Thermal P.C.B.

(1) Remove two screws marked "●" in Figure 7.
(2) Remove all wires from the P.C.B.

3. Removal of Heat Sink, Front Chassis and LED P.C.B

(1) After removal of bottom cover, remove seven screws marked "□" in Figure 5.
(2) Disconnect the connector from LED P.C.B.
(3) Remove heat sink with front chassis and LED P.C.B.

4. Removal of Fuse & Coupler P.C.B and Din & SW P.C.B

(1) After removal of bottom cover, heat sink, remove two screws marked "☆" in Figure 6.
(2) Remove eight screws marked "△" in Figure 4.
(3) Remove solder (a, b) of fuse & coupler P.C.B and din & SW P.C.B.
(4) Disconnect two connectors from there P.C.B.
(5) Fuse & Coupler P.C.B, DIN & SW P.C.B with Rear Cover can be removed completely.

5. Removal Main P.C.B

(1) After removal of fuse & coupler P.C.B and Din & SW P.C.B, remove solder (c ~ f) as shown in Figure 7.
(2) Remove four screws marked "■" in Figure 7.



Figure 4



Figure 5



Figure 6



Figure 7

Adjustment Procedures

- **Power Supply Voltage Adjustment**

(1) Connections



Figure 8

(2) Adjustment Procedures

Adjust solid-state variable resistor VR801 to obtain 54 ± 0.5 V (between T.P. 5 and T.P. 6) on the DC voltmeter.

- **Idle Current Adjustment**

(1) Connections



Figure 9

(2) Adjustment Procedures

Adjust the solid-state variable resistor VR501 to obtain 10 ± 1.0 mV (between T.P. 1 and T.P. 3) on the DC voltmeter. In the same manner, adjust the VR502 to also obtain 10 ± 1.0 mV (between T.P. 2 and T.P. 4) on the DC voltmeter.

- Idle current = 10 ± 1.0 (mV) ÷ 0.2 (ohm) = 50 ± 5.0 (mA)

Adjustment Locations



Main P. C. Board (Top View)

Block Diagram



Parts Layout on P.C. Boards

- **Main P. C. Board (Top View)**

IC201

1	2	3	4	5	6	7	8
0	0	0	−12.0	0	0	0	12.0

IC501 IC502

1	2	3	4	5	6	7	8	9	10	11	12
26.8	26.8	20.5	0.09	0.09	−25.2	−1.08	0.51	−26.9	−26.9	−0.56	0.52

IC801

1	2	3	4	5	6	7	8
2.4	2.4	2.1	0	1.5	3.6	0	14.2
9	**10**	**11**	**12**	**13**	**14**	**15**	**16**
0.9	0.9	14.2	14.2	4.9	4.9	4.9	0

PC802

1	2	3	4
5.8	4.8	8.1	14.2



	E	C	B
Q501	−1.12	0.52	−0.06
Q502	−1.10	0.49	−0.08
Q503	0	0.49	0
Q504	0	0.47	0
Q505	0	−1.0	0
Q506	0	−1.0	0
Q507	0	26.68	0.54
Q508	0	26.82	0.49
Q509	0	−27.65	−0.56
Q510	0	−27.64	−0.55
Q511	0	14.37	0
Q512	0	14.37	0
Q513	14.39	0	14.38
Q514	0	14.53	−3.9
Q515	13.75	13.96	14.51
Q801	13.6	14.28	13.6
Q802	0	0.05	4.9
Q803	4.9	0	4.9
Q804	0	4.9	0.09
Q805	0	0.3	−0.3
Q806	0	0.3	−0.4
Q807	14.2	6.6	14.6
Q808	14.3	7.1	14.7
Q809	0.2	14.3	0.2
Q810	0.2	14.3	0.2
Q811	0	14.3	0.17
Q812	0	14.3	0.17
Q813	0	14.3	0.2
Q814	0	14.3	0.2

- **Main P. C. Board (Bottom View)**



- **DIN and Switch P. C. Board**



(Top View)



(Bottom View)

- **Fuse and Coupler P. C. Board**



(Top View)



(Bottom View)

- **Thermal P. C. Board**



(Top View)



(Bottom View)

- **LED P. C. Board**



(Vop View)



(Bottom View)

Electrical Parts List

Carbon resistors of less than 1/4 watts are not entered on the parts list, so please confirm them using the schematic diagram.

Symbol No.	Part No.	Description
Main P. C. Board		
ICs		
IC201	51T65380F01	BA4558
or	51S43471U02	µPC4558C
IC801	51T71049F01	TL494CN
or	51T70759F01	µPC494C
PC802	51T70760F01	Photo coupler PS2401-1
Transistors		
Q503	48T51091F01	2SC2021
Q504	48T51091F01	2SC2021
Q505	48T63086F01	2SA937M
Q506	48T63086F01	2SA937M
Q511	48T51091F01	2SC2021
Q512	48T51091F01	2SC2021
Q513	48T63086F01	2SA937M
Q514	48T57337F01	2SD1330
Q515	48T51091F01	2SC2021
Q801	48T69177F01	2SA1358
Q802	48T62540F01	UN1211
Q803	48T63086F01	2SA937M
Q804	48T51091F01	2SC2021
Q805	48T51091F01	2SC2021
Q806	48T51091F01	2SC2021
Q807	48T63086F01	2SA937M
Q808	48T63086F01	2SA937M
Diodes		
D501	48T58583F01	SS176TPA7
or	48T68828F01	1SS133
D502	48T58583F01	SS176TPA7
or	48T68828F01	1SS133
D503	48T58583F01	SS176TPA7
or	48T68828F01	1SS133
D504	48T58583F01	SS176TPA7
or	48T68828F01	1SS133
D505	48T58583F01	SS176TPA7
or	48T68828F01	1SS133
D506	48T58583F01	SS176TPA7
or	48T68828F01	1SS133
D507	48T58583F01	SS176TPA7
or	48T68828F01	1SS133
D508	48T58583F01	SS176TPA7
or	48T68828F01	1SS133
D509	48S40477U01	IN4003
D510	48S40477U01	IN4003
D511	48C40235G02	10E2
D801	48T68580F03	DSA3A4-F5
D802	48T68580F03	DSA3A4-F5
D806	48T58593F01	GFD 10-E.G
D807	48T58583F01	SS176TPA7
or	48T68828F01	1SS133
D808	48T58583F01	SS176TPA7
or	48T68828F01	1SS133
D809	48S40477U01	IN4003
ZD201	48T68697F46	Zener, HZS 12EB2
or	48T68699F38	Zener, MTZ 12-B
ZD202	48T68697F46	Zener, HZS 12EB2
or	48T68699F38	Zener, MTZ 12-B
ZD801	48T68697F24	Zener, HZS6.2EB2
or	48T68699F16	Zener, MTZ 6.2-B
ZD802	48T68697F57	Zener, HZS 18EB1
or	48T68699F49	Zener, MTZ 18-A
ZD803	48T68697F66	Zener, HZS 22EB3
or	48T68699F59	Zener, MTZ 22-D
ZD804	48T68697F40	Zener, HZS 10EB3
or	48T68699F33	Zener, MTZ 10-D
Thermistor		
TH802	48T60670F01	20K ohms
Coils		
L501	24T67516F01	Choke, 1.1µH
L502	24T67516F01	Choke, 1.1µH
L802	25T58607F02	Choke, 6A
L803	25T58607F02	Choke 6A
T801	25T47510F01	Choke, Filter, (EI-14)
T802	25T71689F01	Choke, Filter, (EI-19)
or	25C40894G11	Transformer
T803	25T70842F01	Choke,Common 3521

Symbol No.	Part No.	Description
Volume controls		
VR201	18T69022F01	10K ohms
VR501	18B44064J01	470 ohms 1/2W
VR502	18B44064J01	470 ohms 1/2W
VR801	18B44064J02	4.7K ohms 1/2W
Relay		
RL501	80T70844F01	G5R-2232P-12V
Capacitors		
C201	23T42478F26	Electrolytic 2.2µF 50V
C202	23T42478F26	Electrolytic 2.2µF 50V
C203	08S53332F27	CP. 220pF
C204	08S53332F27	CP. 220pF
C209	23S40657F10	Electrolytic 10µF 16V
C210	23S41198U12	Electrolytic 10µF 50V
C211	23S40657F21	Electrolytic 100µF 25V
C212	23S40657F21	Electrolytic 100µF 25V
C501	23T42478F24	Electrolytic 1µF 50V
C502	23T42478F24	Electrolytic 1µF 50V
C503	08S53332F27	CP. 220pF
C504	08S53332F27	CP. 220pF
C505	23S41198U12	Electrolytic 10µF 50V
C507	23T65374F05	Electrolytic 100µF 16V
C508	23T65374F05	Electrolytic 100µF 16V
C509	08S53332F17	CP. 33pF
C510	08S53332F17	CP. 33pF
C513	08S53332F37	CP. 1500pF
C514	08S53332F37	CP. 1500pF
C515	08S53332F37	CP. 1500pF
C516	08S53332F37	CP. 1500pF
C517	08T57705F75	Mylar 0.047µF
C518	08T57705F75	Mylar 0.047µF
C519	08S53332F11	CP. 10pF
C520	08S53332F11	CP. 10pF
C521	08T57705F75	Mylar 0.047µF
C522	08T57705F75	Mylar 0.047µF
C523	23S41192U68	Electrolytic B.P. 100µF 10V
C525	23T65374F05	Electrolytic 100µF 16V

Symbol No.	Part No.	Description
C526	23T68328F92	Electrolytic 1800µF 35V
C527	23T68328F92	Electrolytic 1800µF 35V
C528	23T68328F45	Electrolytic 1000µF 35V
C529	23T68328F92	Electrolytic 1800µF 35V
C530	23T68328F92	Electrolytic 1800µF 35V
C531	23T68328F92	Electrolytic 1800µF 35V
C532	23T68328F92	Electrolytic 1800µF 35V
C533	08S53332F51	CP. 0.022µF
C534	08T50579F21	TF 0.47µF
C535	08S53332F57	CP. 0.1µF
C536	08T42629F71	Mylar 0.022µF
C537	08T42629F71	Mylar 0.022µF
C801	23C42170G30	Electrolytic 470µF 16V
C802	23C42170G30	Electrolytic 470µF 16V
C803	08S40805F22	Ceramic 0.04µF
C804	23T51232F02	Electrolytic 1000µF 16V
C805	23T65374F02	Electrolytic 220µF 10V
C806	23T65374F02	Electrolytic 220µF 10V
C807	08T57705F79	Mylar 0.1µF
C808	08T57705F55	Mylar 1000pF
C809	23T65374F05	Electrolytic 100µF 16V
C810	08S53332F23	CP. 100pF
C811	08S53332F23	CP. 100pF
C812	08S53332F23	CP. 100pF
C813	08S53332F23	CP. 100pF
C814	08S53332F35	CP. 1000pF
C815	08S53332F35	CP. 1000pF
C816	08S40805F22	Ceramic 0.04µF
C817	23C42170G37	Electrolytic 3300µF 16V
C818	23T69238F01	Electrolytic 2400µF 16V
C819	08T57851F05	PF. 0.022µF
C820	08T57851F05	PF. 0.022µF
C822	23T68328F45	Electrolytic 1000µF 35V
C823	23T68328F45	Electrolytic 1000µF 35V
C824	23S40657F27	Electrolytic 0.47µF 50V
C825	08S53332F35	CP. 1000pF
C826	08S53332F35	CP. 1000pF

Symbol No.	Part No.	Description
Resistors		
R201	06S53330F45	CP. 470 ohms 1/8W
R202	06S53330F45	CP. 470 ohms 1/8W
R203	06S53330F53	CP. 1K ohms 1/8W
R204	06S53330F53	CP. 1K ohms 1/8W
R205	06S53331F02	CP. 100K ohms 1/8W
R206	06S53331F02	CP. 100K ohms 1/8W
R209	06S53330F67	CP. 3.9K ohms 1/8W
R210	06S53330F67	CP. 3.9K ohms 1/8W
R211	06S53330F53	CP. 1K ohms 1/8W
R212	06S53330F53	CP. 1K ohms 1/8W
R213	06S53331F02	CP. 100K ohms 1/8W
R214	06S53331F02	CP. 100K ohms 1/8W
R215	06S53330F53	CP. 1K ohms 1/8W
R216	06S53330F53	CP. 1K ohms 1/8W
R501	06S53330F79	CP. 12K ohms 1/8W
R502	06S53330F79	CP. 12K ohms 1/8W
R503	06S53330F61	CP. 2.2K ohms 1/8W
R504	06S53330F61	CP. 2.2K ohms 1/8W
R505	06S53330F93	CP. 47K ohms 1/8W
R506	06S53330F93	CP. 47K ohms 1/8W
R507	06S53330F60	CP. 2K ohms 1/8W
R508	06S53330F60	CP. 2K ohms 1/8W
R509	06S53330F59	CP. 1.8K ohms 1/8W
R510	06S53330F59	CP. 1.8K ohms 1/8W
R511	06S53330F51	CP. 820 ohms 1/8W
R512	06S53330F51	CP. 820 ohms 1/8W
R513	06S53330F41	CP. 330 ohms 1/8W
R514	06S53330F41	CP. 330 ohms 1/8W
R515	06S53330F41	CP. 330 ohms 1/8W
R516	06S53330F41	CP. 330 ohms 1/8W
R517	06S53330F81	CP. 15K ohms 1/8W
R518	06S53330F81	CP. 15K ohms 1/8W
R519	06S53330F81	CP. 15K ohms 1/8W
R520	06S53330F81	CP. 15K ohms 1/8W
R523	06T51107F02	RW. 0.1 ohms 5W
R524	06T51107F02	RW. 0.1 ohms 5W
R525	06T67581F12	C.F. 22 ohms 1/2W
R526	06T67581F12	C.F. 22 ohms 1/2W
R527	06T67581F12	C.F. 22 ohms 1/2W
R528	06T67581F12	C.F. 22 ohms 1/2W
R529	06S53330F79	CP. 12K ohms 1/8W
R530	06S53330F79	CP. 12K ohms 1/8W

Symbol No.	Part No.	Description
R531	06S53330F53	CP. 1K ohms 1/8W
R532	06S53330F65	CP. 3.3K ohms 1/8W
R533	06S53330F77	CP. 10K ohms 1/8W
R534	06S53330F69	CP. 4.7K ohms 1/8W
R535	06S53330F89	CP. 33K ohms 1/8W
R536	06S53330F89	CP. 33K ohms 1/8W
R537	06T67581F24	C.F. 220 ohms 1/2W
R538	06T67581F21	C.F. 120 ohms 1/2W
R541	06T67581F08	C.F. 10 ohms 1/2W
R542	06T67581F08	C.F. 10 ohms 1/2W
R543	06S53330F05	CP. 10 ohms 1/8W
R544	06S53330F05	CP. 10 ohms 1/8W
R545	06S53330F05	CP. 10 ohms 1/8W
R546	06S53330F05	CP. 10 ohms 1/8W
R547	06S53330F53	CP. 1K ohms 1/8W
R801	06S53330F65	CP. 3.3K ohms 1/8W
R802	06S53330F65	CP. 3.3K ohms 1/8W
R803	06S53330F53	CP. 1K ohms 1/8W
R804	06S53330F77	CP. 10K ohms 1/8W
R805	06S53331F19	CP. 510K ohms 1/8W
R806	06S53330F77	CP. 10K ohms 1/8W
R807	06S53330F84	CP. 20K ohms 1/8W
R808	06S53330F37	CP. 220 ohms 1/8W
R809	06S53330F84	CP. 20K ohms 1/8W
R811	06S53330F65	CP. 3.3K ohms 1/8W
R812	06S53331F02	CP. 100K ohms 1/8W
R813	06S53330F96	CP. 62K ohms 1/8W
R814	06S53330F65	CP. 3.3K ohms 1/8W
R815	06S53330F77	CP. 10K ohms 1/8W
R816	06S53330F83	CP. 18K ohms 1/8W
R817	06S53330F94	CP. 51K ohms 1/8W
R818	06S53330F94	CP. 51K ohms 1/8W
R819	06S53330F70	CP. 5.1K ohms 1/8W
R820	06S53330F70	CP. 5.1K ohms 1/8W
R821	06S53330F94	CP. 51K ohms 1/8W
R822	06S53330F94	CP. 51K ohms 1/8W
R823	06S53330F70	CP. 5.1K ohms 1/8W
R824	06S53330F70	CP. 5.1K ohms 1/8W
R827	06S53330F47	CP. 560 ohms 1/8W
R828	06S53330F47	CP. 560 ohms 1/8W
R829	06S53330F43	CP. 390 ohms 1/8W
R830	06S53330F43	CP. 390 ohms 1/8W
R831	06T55178F07	MF 1.0 ohm 1W
R832	06T55178F07	MF 1.0 ohm 1W
R833	06T55175F17	MF 10 ohms 1/2W
R834	06T55175F17	MF 10 ohms 1/2W
R835	06T55177F17	MF 10 ohms 1W

Symbol No.	Part No.	Description
R836	06T55177F17	MF 10 ohms 1W
R842	06S53330F69	CP. 4.7K ohms 1/8W
R843	06S53330F53	CP. 1K ohms 1/8W
R845	06S53330F77	CP. 10K ohms 1/8W
R846	06S53330F43	CP. 390 ohms 1/8W
R847	06S53330F43	CP. 390 ohms 1/8W
R848	06S53330F61	CP. 2.2K ohms 1/8W
R849	06S53330F94	CP. 51K ohms 1/8W
R850	06T55178F07	MF 1.0 ohm 1W
R851	06T55178F07	MF 1.0 ohm 1W
Thermal P. C. Board		
Thermistors		
TH803	48T60670F01	20K ohms
TH804	48T60670F01	20K ohms
Diodes		
D810	48T58583F01	SS176TPA7
or	48T68828F01	1SS133
D811	48T58583F01	SS176TPA7
or	48T68828F01	1SS133
D812	48T58583F01	SS176TPA7
or	48T68828F01	1SS133
D813	48T58583F01	SS176TPA7
or	48T68828F01	1SS133
Miscellaneous		
ICs		
IC501	51T58602F01	μPC 1225H
IC502	51T58602F01	μPC 1225H
Transistors		
Q501	48T64376F01	2SC3423
Q502	48T64376F01	2SC3423
Q507	48T58609F01	2SC3182
Q508	48T58609F01	2SC3182
Q509	48T58610F01	2SA1265
Q510	48T58610F01	2SA1265
Q809	48T40469U01	2SC1983
Q810	48T40469U01	2SC1983
Q811	48T47613F01	2SD1065
Q812	48T47613F01	2SD1065
Q813	48T47613F01	2SD1065
Q814	48T47613F01	2SD1065

Symbol No.	Part No.	Description
Diodes		
D803	48T68079F03	30D4 FA
D804	48T71360F01	C10P20F
or	48T61597F01	CTG22S
D805	48T71360F02	C10P20FR
or	48T61597F02	CTG22R
LED		
LD801	48T52238F02	PR5552K (Red)
Switches		
S201	40T70757F01	Slide (Variable/Fix)
S202	40T70757F01	Slide (SP SW 4 ohms/ 2 ohms)
Transformer		
T804	25T70843F01	DC-DC Control
Others		
E501	01T70747F01	Assy., Coupler 4-pins
E801	01T70748F01	Assy., Coupler 6-pins
F801	65T58596F07	Fuse, Auto 25A
F802	65T58596F01	Fuse, Auto 3A
F803	65T58596F01	Fuse, Auto 3A
J201	09T70752F01	Socket, Din 8-pins
J202	09T70753F01	Jack, Rca 2-pins
TH801	48T60670F01	Thermistor, 20 ohms

Schematic Diagram

ICs	IC201 IC501 IC502 PC802 IC801
Transistors	Q501–Q506 Q507–Q510 Q805–Q808 Q809–Q814 Q511 Q512 Q513 Q514 Q515 Q801–Q804
Diodes	ZD201 D501 D503 D505 D507 D511 ZD803 ZD804 D806 D807 D808 D804 D805 D810–D811 ZD202 D502 D504 D506 D508 D509 D510 ZD801 D809 ZD802 D801–D803 LD801



Voltage measuring conditions

Supply voltage	14.4V DC
Measuring instrument	Digital Multimeter
Measuring standard	With respect to the primary ground potential (POWER) With respect to the secondary ground potential (AMPLIFIER)
Measuring conditions	No signal input

Wiring Diagram



Exploded View



Mechanical Parts List

Sym-bol No.	Index	Part No.	Description
1	5C	*	Assy., Main Board 3521
2	5B	01D61220F26	Assy., Connector 3-pins
3	3E	*	Fuse and Coupler P.C.B.
4	5D	*	Cover, Bottom 3521
5	2D	*	Heat, Sink 3521
6		03S44205G04	Screw, Pan (M3 x 5)
7		03S63857F39	Screw, Tapping (M3 X12)
8		03S63857F36	Screw, Tappinpg (M3 x 6)
9		03S71031F08	Screw, Bind (M3 x 5)
10	5E	*	Insulator, Cover
11	6C	15B70599F01	Cover LED
12	3G	27C70598F03	Chassis, Rear
13	3H	03S43997P51	Screw, Round (M2.6x4)
14	3G	03S68555F02	Screw, Pan (M2.5 x 5.5)
15	3H	03S40012G41	Screw, Tapping (M3 x 8)
16	3G	14A70605F01	Insulator, Switch Lock
17	5B	27C70597F02	Chassis, Front
18		*	Heat, Sink IC "A"
19		03S71031F07	Screw, Bind (M3 x 6)
20	4D	26A72624F01	Shield, Case
21	4D	75S72374F06	Cushion, Rubber
22		*	Heat, Sink Transistor A
23		03S71252F05	Screw, Pan (M3 x 10)
24		03S71252F04	Screw, Pan (M3 x 9)
25	5C	*	LED P.C.B.
26	3C	*	Heat, Sink
27	4C	03S71252F03	Screw, Pan (M3 x 8) (Used when D804 and D805 are C10P20)
or	4C	03S71252F05	Screw, Pan (M3 x 10) (Used when D804 and D805 are CTG22)
28	3F	09T70751F01	Holder, Auto Fuse 1-pin
29	4F	*	DIN and Switch P.C.B.
30	4D	*	Assy., Thermal P.C.B.
31	5D	*	Bracket, P.C.B.
32		07R51146F01	Bracket, Thermistor
33	4E	29C41045P05	Lug, Wrap

*** The parts without part number are not supplied.**

Packing Method View



Packing Parts List

Symbol No.	Part No.	Description
		Packing Assembly Parts
101	01V71300F62	Assy, Kit Installation 3519
□ 102	01V71300F10	Assy, Pamphlet
△ 102	68P73333F20	Owner's manual
103	56S69254F15	Carton, Packing Individual Std
104	56D70744F01	Tray, Packing "Front"
105	56D70744F02	Tray, Packing "Rear"
106	56B72811F02	Sack, Polyethylene
107	01T70749F01	Assy, Kit Wire 4-pins
108	01T71365F01	Assy, Kit Wire 6-pins
Labels		
	54S60911F92	Composite (Cover Bottom)
	54B42124G01	Serial No. (Cover Bottom, Carton Ind)

□ for AO model only, △ for GO model only, Others; common

Semiconductors Leads Identifications

BA4558
μPC4558 IC201





μPC494C
TL494CN IC801





μPC1225H IC501, IC502





PC2401 IC802





2SC3423 Q501, Q502



2SC2021 Q503, Q504, Q511, Q512, Q515, Q804
Q805, Q806
2SA937 Q505, Q506, Q513, Q803, Q807, Q808



2SC3182 Q507, Q508
2SA1265 Q509, Q510



2SD1330 Q514



2SA1358 Q801



UN1211(48T62540F01) Q802





2SC1983 Q809, Q810



2SD1065 Q811, Q812, Q813, Q814



Schematic Diagram

ICs	IC201 IC501 IC502 PC802 IC801
Transistors	Q501–Q506 Q507–Q510 Q805–Q808 Q809–Q814 Q511 Q512 Q513 Q514 Q515 Q801–Q804
Diodes	ZD201 D501 D503 D505 D507 D511 ZD803 ZD804 D806 D807 D808 D804 D805 D810–D811 ZD202 D502 D504 D506 D508 D509 D510 ZD801 D809 ZD802 D801–D803 LD801



Voltage measuring conditions

Supply voltage	14.4V DC
Measuring instrument	Digital Multimeter
Measuring standard	With respect to the primary ground potential (POWER) With respect to the secondary ground potential (AMPLIFIER)
Measuring conditions	No signal input